



4184 E. Conant St.
Long Beach, CA 90808
Tel. 888-900-1002
Fax. 310-900-1088
www.turboairinc.net

Project :

Model # :

Item # :

Qty :

Approval :

Extended Thin Profile Coil


Model : TTA130AE(OX, NX, OM, NM)



FEATURES / BENEFITS



Blue Anti-Corrosion
Hydrophobic Coated Fin.
Air Pass Guard for Better
Efficiency.



Inner Groove Copper Tube
for Maximum Coil Efficiency.
Mounted TXV, Solenoid,
Thermostat(Optional).

MODEL CAPACITY

- Air Defrost Coil: 5600(2 Fan) ~ 17500BTU(6 Fan)
- Electric Defrost Coil: 4900(2 Fan) ~ 13800BTU(6 Fan)

Extended Thin Profile Coil

Model : TTA130AE(0X, NX, OM, NM)

TTA AIR DEFROST MODEL 60HZ WITH EC MOTOR (DUAL SPEED)

Capacity (R-404A)				Capacity (R-448A / R-449A)				Fan Data		
10°F / 6°C TD 25°F / - 4°C SST		14°F / 8°C TD 21°F / -6°C SST		10°F / 6°C TD 25°F / - 4°C SST		14°F / 8°C TD 21°F / -6°C SST		CFM/m³H		No.
BTUH	Watts	BTUH	Watts	BTUH	Watts	BTUH	Watts			
13053	3823	19151	5609	13014	3812	19086	5590	2231	3791	3

EC Motor Data			Connections (Inches)				Approx. Net Weight (Lbs. / Kg)	AWEF Value	
115V 1Ph 60Hz								R-404A	R-448A / R-449A
HP	Total Amps	Watts	COIL INLET	SUCTION	EQUALIZER	DRAIN			
1/25	2.25	75	1/2 OD	5/8 ID	1/4 OD	3/4 MPT	61 / 28	9.00	9.00

No. of Fans	Dimensions (Inches / mm)			
	A	B	C	D
3	69.4 (1764)	60.6 (1539)	-	-

Design and specifications subject to change without notice

TTA130AEOX: R404A TXV "SBFSE-A-C" (Inlet: 3/8", Outlet: 1/2") Pre-installed

TTA130AENX: R448A/R449A TXV "SBFDE-A-C" (Inlet: 3/8", Outlet: 1/2") Pre-installed


TTA130AEOM: R404A TXV "SBFSE-A-C" (Inlet: 3/8", Outlet: 1/2") & LLSV "E3S130" (3/8") Pre-installed

TTA130AENM: R448A/R449A TXV "SBFDE-A-C" (Inlet: 3/8", Outlet: 1/2") & LLSV "E3S130" (3/8") Pre-installed


■ **WARRANTY : 1 Year Fan Motor and Parts Warranty**

PLAN VIEW

(unit : inch)



FRONT VIEW



RIGHT SIDE VIEW



■ Toll Free: 888-900-1002

Turbo air

GERMAN KNIFE

RADIANCE

Turbo air

texaking

"Subject to change without notice" will allow Turbo Air to not be liable for small changes such as amperage, size or any other issue that someone would blame on us.